

2013

AN INVESTIGATION OF ELECTROMYOGRAPHIC (EMG) CONTROL OF DEXTROUS HAND PROSTHESES FOR TRANSRADIAL AMPUTEES

Ali, Ali Hussian

<http://hdl.handle.net/10026.1/2860>

<http://dx.doi.org/10.24382/3389>

University of Plymouth

All content in PEARL is protected by copyright law. Author manuscripts are made available in accordance with publisher policies. Please cite only the published version using the details provided on the item record or document. In the absence of an open licence (e.g. Creative Commons), permissions for further reuse of content should be sought from the publisher or author.

Section 4.1). According to Farrell (2011), the new optimal controller delay (see **Eq. A.1**) for an example window of 100 ms window size, 1.3 ms processing time and 9 votes is 501.3ms which 5 times larger than the estimated based on the old estimation proposed by (Englehart and Hudgins 2003) (see **Eq. A.2**). This delay exceeds the acceptable level of controller delay which is between 100 and 128 ms (Farrell and Weir 2007).

$$D = \left(\frac{n+1}{2}\right) T_a + \tau \quad \text{A-1}$$

where D is the optimal controller delay, n is the number of majority votes, T_a is the analysis window length and τ is the processing time

$$n \times T_{new} \leq 300 \text{ ms.} \quad \text{A-2}$$

where n is number of majority votes, T_{new} is the window overlap and τ is the processing time.

According to **Eq. A.2** (Chan and Englehart 2003; Englehart and Hudgins 2003; Chan and Englehart 2005), the optimal controller delay is $4 \times 50 = 200$ ms. However, the original equations proposed by Englehart were called into question by Farrell (2011) (see **Eq. A.3** for detached segmentation scheme). According to Farrell (2011), the new optimal controller delay (see **Eq. A.3**) for an example of 150 ms window size, 50 ms window overlap and 10 votes is $325 + \tau$ ms which larger than the acceptable level of controller delay which suggest that this processing chain may not be suitable for the real-time implementation (Farrell and Weir 2007).

$$D = \frac{1}{2} T_a + \frac{n}{2} T_{new} + \tau \quad \text{0-3}$$

where D is the optimal controller delay, n is the number of majority votes, T_a is the analysis window length, T_{new} is the window overlap and τ is the processing time.

Appendix- B

Negentropy:

Negentropy is a measure based on the information theoretic quantity of (differential) entropy. The value of Negentropy is zero for a Gaussian variable and is always non-negative for other distributions (Nazarpour, Sharafat et al. 2005). The Negentropy is given by

$$J(x) = H(x_{Gauss}) - H(x) \quad C-1$$

where J is the Negentropy, H is the entropy and x_{Gauss} is a Gaussian random variable with the same covariance matrix as x .

References for the appendixes

- Chan, A. and K. Englehart (2003). Continuous classification of myoelectric signals for powered prostheses using gaussian mixture models. 25th Annual International Conference of the IEEE Engineering in Medicine and Biology Society. 3: 2841-2844 Vol.2843.
- Chan, A. and G. Green (2007). Myoelectric control development toolbox. 30th Conference of the Canadian Medical & Biological Engineering Society. Toronto, ON.
- Chan, A. D. C. and K. B. Englehart (2005). "Continuous myoelectric control for powered prostheses using hidden Markov models." Biomedical Engineering, IEEE Transactions on 52(1): 121-124.
- Englehart, K. and B. Hudgins (2003). "A robust, real-time control scheme for multifunction myoelectric control." IEEE Transactions on Biomedical Engineering 50(7): 848-854.
- Englehart, K., B. Hudgins, et al. (2003). "Continuous multifunction myoelectric control using pattern recognition." Technology and Disability 15(2): 95-103.
- Farrell, T. R. (2011). "Determining delay created by multifunctional prosthesis controllers." Journal of Rehabilitation Research & Development (JRRD) Guest Editorial 48(6).
- Farrell, T. R. and R. F. Weir (2007). "The optimal controller delay for myoelectric prostheses." IEEE Transactions on Neural Systems and Rehabilitation Engineering, 15(1): 111-118.
- Nazarpour, K., A. R. Sharafat, et al. (2005). Negentropy analysis of surface electromyogram signal. 13th IEEE Workshop on Statistical Signal Processing (IEEE/SP) 974-977.
- Simon, A. M. and L. J. Hargrove (2011). A comparison of the effects of majority vote and a decision-based velocity ramp on real-time pattern recognition control. Engineering in Medicine and Biology Society, EMBC, 2011 Annual International Conference of the IEEE.
- Smith, L. H., L. J. Hargrove, et al. (2011). "Determining the Optimal Window Length for Pattern Recognition-Based Myoelectric Control: Balancing the Competing Effects of Classification Error and Controller Delay." IEEE Transactions on Neural Systems and Rehabilitation Engineering 19(2): 186-192.